



- High band capable, ensuring that your installation can receive all signals.
- Simple and more cost effective installation.
- 30 user bands, 3 unicable outputs and 1 universal output.
- Multiple decoders can be connected to the DStv Smart LNB without the need for a multiswitch / DStv Switch.
- Non used unicable parts must be terminated.

## DStv Smart LNB

The DStv Smart LNB has been designed and manufactured for DStv installations where customers make use of their own satellite dish. It is not generally suitable for multiple unit dwellings (like complexes and apartments) or commercial customers. It combines the features of a DStv Switch installation and is recommended for all DStv Explora and most XtraView installations.

## TECHNICAL INFORMATION

### SPECIFICATIONS

Difference between the Old and New Dstv Smart LNB		
	OLD	NEW
Model Number	LMX500	LMX501
Warranty	12 months	12 months
LNB Dimensions	168mm X 142mm	132.2mm X 107.8mm
User Bands	24	30
UniCable Outputs	4	3
Universal Outputs	2	1
Input Frequency	10.7 – 12.75 GHz	10.7 – 12.75 GHz
Output Frequency	950 – 2150 MHz	750 – 2350 MHz
L01	9.75 GHz	9.75 GHz
L02	10.6 GHz	10.6 GHz

## THE PACKAGE CONTAINS

1 x DStv Smart LNB

## PACKAGE DIMENSIONS



	Height (mm)	Depth (mm)	Width (mm)	Weight (kg)	QTY
Gift Box	61	136	113	0.26	1
Bulk Carton	560	321	258	13.16	40